

LF-FMR080YSIII

FMR*YSIII non-SELV 1-driver with 8-output current | Constant Current - Non Dimmable



Product family features

- Low THD<15%@full load
- Rated input voltage: 220-240Vac
- Ta: -40℃~+60℃
- Ripple current<5%
- Suitable for Class I light fixtures
- 5 years guarantee



Product family benefits

- Output current adjustable via DIP switch in 8 shifts
- Super high efficiency
- Linear metal casing with 21mm housing height
- Long lifetime and high reliability
- Flicker free
- Non-SELV output

Typical applications

- For linear light, tri-proof light and strip light
- For office, commercial, and decorative lighting

Product parameters

- Output current 200/250/300/350/400/450/500/550mA
- Output power 11-80W
- Input voltage 176-264Vac

- Output voltage 54-230Vdc
- Efficiency 94%

Electrical data

Input data	
Rated input voltage	220 240V
AC voltage range	176264V ¹⁾
Mains frequency	0/50/60Hz
Input voltage DC	180 264V ²⁾
Power factor	≥0.98
Efficiency	94% ³⁾
THD	≤15%
Input current	0.55A Max
Inrush current	45A ⁴)
Loading number on circuit breaker 10 A (B)	13
Loading number on circuit breaker 10 A (C)	21
Loading number on circuit breaker 16 A (B)	21
Loading number on circuit breaker 16 A (C)	35
Loading number on circuit breaker 20 A (C)	43
Loading number on circuit breaker 25 A (C)	54
Protective conductor current	≤3.5mA
Output data	
Nominal output voltage	54 230V ⁵⁾
Nominal output current	200/250/300/350400/450/500/550mA ⁶⁾
Default output current	550mA
Current setting	DIP switch (please see the DIP switch definition)
Maximum output power	80W
Nominal output power	11 80W
Output ripple current (100 Hz)	<5%
Flicker	According to IEEE Std 1789-2015
CIESVM	≤0.4
IEC-Pst	≤1
Output current tolerance	±5%
Temperature tolerance	±10%
Start-up time	<0.5S
Safety	
Withstanding voltage	I/P-PG: 1.6kV&5mA&60S;
Surge capability (L-N)	1kV
Surge capability (L/N-Ground)	2kV
Insulation resistance	I/P-PG O/P-PG: >100MΩ@500VDC
Guarantee	5 years ⁷⁾

1) 176V can be used for a short time when the power grid fluctuated, and the maximum use time is 4H. It is not recommended to use 176V under the normal use environment for a long time

2) DC input is only for emergency

3) @350mA/230V

4) t =180µs

5) Please refer to the operating window about the relationship between output voltage and output current

6) Fixed current version optional

7) **5 years @Tc≤ 83**°C

Note: single harmonic is NG for 25-30W input power, while single harmonic is OK for other power

Characteristic diagrams



Typical Power Factor vs Load



Typical THD vs Load

Lifespan



Dimensions



Mounting hole spacing, length	200.0mm
Positioning hole diameter	4.2mm
Product weight	150.0g
Cable cross-section, input side	0.5 1.5 mm²
Cable cross-section, output side	0.5 1.5 mm ²
Wire preparation length, input side	7 8mm
Wire preparation length, output side	7 8mm
Length	210.0mm
Width	30.0mm
Height	21.0mm
Colors & materials	

Casing material	Color coated galvanized sheet
Casing color	White

Temperature & operating conditions

Ambient temperature range	-40 °C - +60 °C
---------------------------	-------------------------------

Maximum temperature at Tc test point	90°C
Temperature range at storage	-40 $^\circ \rm C$ - +80 $^\circ \rm C$ (6 months in Class I environment)
Humidity range at storage	20-95%RH (no condensation)
Humidity during operation	20-90%RH
RoHS	RoHS 2.0 (EU) 2015/863

Tc test point

	80
• tc	

Note: this diagram is the front view and Tc point is on the front side of the driver.

Product terminal

	Input		Output
AC-L	AC live wire input	LED+	Positive terminal output of LED driver
AC-N	AC neutral wire input	LED-	Negative terminal output of LED driver
	Earth wire		

DIP switch definition

Output current	Output voltage	DIP switch 1	DIP switch 2	DIP switch 3
200mA	54-230Vdc	-	-	-
250mA	54-230Vdc	-	-	ON
300mA	54-230Vdc	-	ON	-
350mA	54-230Vdc	-	ON	ON
400mA	54-200Vdc	ON	-	-
450mA	54-177Vdc	ON	-	ON
500mA	54-160Vdc	ON	ON	-
* 550mA	54-145Vdc	ON	ON	ON

Note: "-": shift OFF. "*": default current. When adjusting the output current via the DIP switch, please disconnect input AC first so as to use the DIP switch without the input AC connected.

Capabilities

Over-temperature protection	-
Overload protection	-

Short circuit protection	Automatic reversible
No-load protection	<250V
Suitable for fixtures with prot. class	I
Control interface	-
Number of channels	1 channel

Programming

Programmer	-
DALI control software	-
APP	-

Certificates & standards

Approval marks	ENEC, UKCA, CE, CB, EL, RCM, SAA, EAC, CCC
	GB 19510.1-2009, GB 19510.14-2009
	IEC/EN 61347-2-13, IEC/EN 61347-1, IEC/EN 62493
Standards	IEC/EN 62384
	IEC/EN 61347-2-13 Annex J
	AS 61347.1, AS 61347.2.13
ENG	TP TC 004/2011+TP TC 020/2011
	GB 17625.1-2022, GB/T 17743-2021
	EN 55015, EN 61547, EN 61000-3-2,3
Type of protection	IP20

Logistical data

Product	Packaging unit	Dimensions (L*W*H)	Volume	Gross weight
	(Pieces/Unit)			
LF-FMR080YSIII	63	385mm*285mm*210mm	23.04 dm ³	10.02kg±5%

Test equipment & condition

	AC power source: CHROMA6530, digital power meter: CHROMA66205, oscilloscope: Tektronix
	DPO3014, DC electronic load: M9712B, LED board, constant temperature and humidity chamber,
Test equipment	lightning surge generator: Everfine EMS61000-5B, rapid group pulse generator: Everfine
	EMS61000-4A, spectroanalyzer: KH3935, hi-pot tester: EEC SE7440, flicker tester (flicker-free
	coefficient test): Everfine LFA-3000, etc.

If there are no special remarks, the above parameters are tested at the ambient temperature of 25° C, humidity of 50%, maximum output power and input voltage of 230Vac/50Hz.

Additional information

1. It is recommended that user install the over voltage protection, under voltage protection and surge protection devices in the power supply circuits of light fixtures to ensure electricity safety.

2. The LED driver used in combination with the end device is one of the accessories of the whole light fixture, and the EMC of the whole light fixture is not only susceptible to the driver itself, but to the LED light fixture and the whole light fixture's wiring. Thus, the manufacturer of LED light fixture should re-confirm the EMC of the whole light fixture before the whole light fixture is finished.

3. The number of LED drivers that can be connected to a circuit breaker and the inrush current are tested under the same conditions.

4. The PC cover, casing and end cap for assembling the LED driver in the light fixture must meet the fire rating of UL94-V0 or above.

5. The withstand voltage between LEDs and PCBA should be >3KV.

6. It is recommended to install double-pole switch at AC input terminal. If user uses the single-pole switch, make sure to connect it to wire L (live wire), otherwise the afterglow of light fixture would be incurred after the AC is disconnected.

7. Because there is parasitic capacitance between LEDs and the PCBA, there will be a slight flicker when the PCBA (the light fixture) is grounded and AC is powered on. It's normal for non-isolated products. To avoid this phenomenon, please choose a light board with lower parasitic capacitance.

8. The light panel, fixed bracket and driver grounding should be secure.

Transportation & storage

Suitable transportation means: vehicles, boats and aeroplanes.

In transit, it is necessary to prepare awnings for rain or sun protection. Moreover, please keep civilized loading and unloading to prevent the vibration or impact on LED driver as much as possible.

The storage of LED driver shall conform to the standard of Class I environment. When using LED drivers which have been stored for more than 6 months, please re-test them firstly. Do not use them unless they are tested to be qualified.

Cautions

Please use Lifud LED driver according to its parameters in the specification, otherwise the LED driver may malfunction. Using any incompatible light fixtures or those that have not been certified may cause fire, explosion or other risks. Man-made damage is beyond the scope of Lifud warranty service.

Disclaimer

Subject to change without notice. Errors and omissions excepted. Always make sure to use the most recent release. Lifud Technology Co., Ltd. reserves the right to interpret any content of this specification.